

00169.002196

PATENT APPLICATION



IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re application of:

Peter Alleine FLETCHER, et al.

Application No.: 09/983,031

Filed: October 22, 2001

For: METHOD FOR GENERATING AND
DETECTING MARKS

)
: Examiner: Unassigned
)
: Group Art Unit: 2621
)
:
)
:
) January 14, 2002
:

The Commissioner for Patents
Washington, D.C. 20231

RECEIVED
JAN 16 2002
Technology Center 2600

SUBMISSION OF PRIORITY DOCUMENT

Sir:

In support of Applicants' claim for priority under 35 U.S.C. § 119, enclosed
is a certified copy of the following Australian application:

PR 1050, filed October 27, 2000.

Applicants' undersigned attorney may be reached in our Washington office by telephone at (202) 530-1010. All correspondence should continue to be directed to our address given below.

Respectfully submitted,



Attorney for Applicants
Registration No. 36,570

FITZPATRICK, CELLA, HARPER & SCINTO
30 Rockefeller Plaza
New York, New York 10112-3801
Facsimile: (212) 218-2200
BLK/cmv



10/22/01
Peter allene FLETCHER,
et al.



Patent Office
Canberra

RECEIVED

JAN 16 2002

Technology Center 2600

I, GAYE TURNER, TEAM LEADER EXAMINATION SUPPORT AND SALES hereby certify that annexed is a true copy of the Provisional specification in connection with Application No. PR 1050 for a patent by CANON KABUSHIKI KAISHA filed on 27 October 2000.

I further certify that pursuant to the provisions of Section 38(1) of the Patents Act 1990 a complete specification was filed on 19 October 2001 and it is an associated application to Provisional Application No. PR 1050 and has been allocated No. 81525/01.

WITNESS my hand this
Fifth day of November 2001

GAYE TURNER
TEAM LEADER EXAMINATION
SUPPORT AND SALES



**CERTIFIED COPY OF
PRIORITY DOCUMENT**

ORIGINAL

AUSTRALIA

Patents Act 1990

PROVISIONAL SPECIFICATION FOR THE INVENTION ENTITLED:

Method for Generating and Detecting Marks


Name and Address of Applicant:

Canon Kabushiki Kaisha, incorporated in Japan, of 30-2, Shimomaruko 3-
chome, Ohta-ku, Tokyo, 146, Japan

Names of Inventors:

Peter Alleine Fletcher
Kieran Gerard Larkin

This invention is best described in the following statement:



METHOD FOR GENERATING AND DETECTING MARKS

Technical Field of the Invention

The present invention relates to the generation, embedding and detection of patterns in images, audio streams, video, and documents or surfaces of articles. Such embedded patterns may be used for invisible watermarking, and/or for alignment
5 information. In particular, the present invention relates to embedded patterns that have scale and rotation invariant properties.

Background Art

With the advent of digital images and digital image distribution, protection of such
10 digital images against unauthorised copying has become an issue for image publishers and authors. One technique used to identify the ownership of an image is to embed a pattern or patterns into the image, such that the embedded pattern is not visible to the naked eye of an observer. Such a pattern is called a watermark. The presence of the watermark can be detected in the copied image by the owner of the original image, thereby proving their
15 ownership.

Systems are known for embedding a pattern or patterns into an image or document. However, present methods of invisible watermarking of documents and images are often very sensitive, therefore not robust, to geometric image distortions. The most common image distortions are changes in the magnification or scaling, changes to
20 the orientation of the image or rotation, and losing edge information of the image or cropping.

Known methods which are robust to such changes, are either incapable of storing significant amounts of data in the watermark, or are susceptible to malicious intervention for the reason that the pattern is easily detected by simple spectral methods. One such spectral method is an analysis of the Fourier magnitude peaks of the image with an
5 embedded watermark.

One of the most popular and effective methods for detecting patterns is correlation. In fact, for linear systems, correlation, or matched filtering, can be shown to be mathematically, an optimal detection method. Unfortunately correlation in two dimensions is not, in general, invariant with orientation or scaling.

10 It should be noted that correlation can only give well defined and easily distinguished correlation magnitude peaks if the underlying pattern has a broad Fourier magnitude distribution. This is a consequence of the uncertainty principle. Therefore, patterns with very sharp or constrained Fourier magnitudes, such as a narrow-bandpass function, are ill equipped for correlation purposes.

15 Rotation invariance in known systems is typically achieved by using circular symmetric patterns. Alternatively the correlation can be repeated many times with the test pattern at many different orientations, so that at least one correlation is close to the actual orientation. Scale related problems are usually solved by repeated correlations at many different scales so that at least one correlation is close to the actual scale. Such methods
20 are impractical, and as a consequence, correlation seldom is used in cases when arbitrary rotation and/or scaling is present.

Disclosure of the Invention

It is an object of the present invention to substantially overcome, or at least ameliorate, one or more disadvantages of existing arrangements.

According to a first aspect of the invention, there is provided a method of
5 watermarking an image, said method comprising the step of:

mathematically adding at least one basis pattern to said image, wherein said basis pattern(s) is scale and rotation invariant within a complex multiplicative constant.

According to a second aspect of the invention, there is provided a method of
detecting a pattern in a watermark of an image, said watermark comprising at least one
10 basis pattern, with said pattern and said basis pattern(s) being scale and rotation invariant
within a complex multiplicative constant, said method comprising the steps of:

correlating said image with said pattern; and

locating one or more magnitude peaks, said peak(s) corresponding to center
position(s) of basis pattern(s) having the same parameters as that of said pattern.

15 According to a third aspect of the invention, there is provided a method of adding
registration marks to an image, said method comprising the step of:

mathematically adding a plurality of basis patterns to said image, wherein at least
two of said basis patterns are added with different offsets relative to a center of said
image, and said basis patterns are scale and rotation invariant within a complex
20 multiplicative constant.

According to a fourth aspect of the invention, there is provided a method of
registering an image having a watermark embedded, said watermark comprising a
plurality of basis patterns, said method comprising the steps of:

correlating said image with a pattern; said pattern and said basis patterns being scale and rotation invariant within a complex multiplicative constant;

locating peak positions, said peak positions corresponding to center positions of basis patterns having the same parameters as that of said pattern;

5 comparing said peak positions with predetermined positions from an original image; and

transforming said image to invert linear transformations.

According to a fifth aspect of the invention, there is provided a method of watermarking an audio stream, said method comprising the step of:

10 mathematically adding at least one basis signal to said audio stream, wherein said basis signal(s) is scale invariant within a complex multiplicative constant.

According to a sixth aspect of the invention, there is provided a method of detecting a signal in a watermark of an audio stream, said watermark comprising at least one basis signal, with said signal and said basis signal(s) being scale invariant within a
15 complex multiplicative constant, said method comprising the steps of:

correlating said audio stream with said signal; and

locating one or more magnitude peaks, said peak(s) corresponding to center position(s) of basis signal(s) having the same parameter as that of said signal.

According to another aspect of the invention, there is provided an apparatus for
20 implementing any one of the aforementioned methods.

According to another aspect of the invention there is provided a computer program product including a computer readable medium having recorded thereon a computer program for implementing any one of the methods described above.

Brief Description of the Drawings

A number of embodiments of the present invention will now be described with reference to the drawings, in which:

Fig. 1 shows a section of a scale invariant function;

5 Figs. 2A and 2B show the real and imaginary parts of a logarithmic radial phase function having an annular region defined by minimum and maximum radii;

Figs. 3A and 3B show the real and imaginary parts of a logarithmic radial harmonic phase function;

Fig. 4 shows a schematic diagram of a process of watermarking an image;

10 Fig. 5 shows an example watermark pattern;

Fig. 6 shows an example image with the watermark pattern of Fig. 5 embedded using the process of Fig. 4;

Fig. 7A shows a schematic diagram of an alternative process of watermarking an image using de-emphasis;

15 Fig. 7B shows the example image with the watermark pattern of Fig. 5 embedded using the process of Fig. 7A;

Fig. 8 shows a schematic diagram of a process of detecting a watermark in an image;

20 Fig. 9 shows a schematic diagram of an alternative process of detecting a watermark in an image using emphasis;

Fig. 10A shows the magnitude image of correlating the image of Fig. 6 with the correct pattern using the detection process of Fig. 8;

Fig. 10B shows details of one of the magnitude peaks of Fig. 10A;

Fig. 11A shows the magnitude image of correlating the image of Fig. 7B with the correct pattern using the detection process of Fig. 9;

Fig. 11B shows details of one of the magnitude peaks of Fig. 11A;

Fig. 12 shows the example image of Fig. 6 rotated, scaled and cropped;

5 Fig. 13 shows the result of correlating the image of Fig. 12 with the correct pattern using the detection process of Fig. 9;

Fig. 14 shows details of one of the magnitude peaks of Fig. 13; and

Fig. 15 shows a schematic block diagram of a system.

10

Detailed Description

Basic properties of a group of functions, including their correlation properties, will first be described. Processes for watermarking, watermark detection, and apparatus follows the description of the basic properties of those functions.

15 Certain functions have a scale invariant property, whereby a change of scale in the coordinate results in a transformed function that is the same as the original function, apart from a multiplicative constant. These functions are sometimes referred to as homogeneous functions. Consider a homogeneous function:

$$f(r) = \cos[\alpha \ln(r)] \quad (1)$$

having a logarithmic phase as follows:

20 $\psi(r) = \alpha \ln(r) \quad (2)$

Such a phase has a frequency of $\frac{d\psi}{dr} = \frac{\alpha}{r}$. The function $f(r)$ has the useful scaling property, in that:

$$f(ar) = \cos[\alpha \ln(ar)] = \cos[\alpha \ln(r) + \alpha \ln(a)] \quad (3)$$

In other words, a coordinate scale change only produces a fixed phase change in the cosine, providing the scale invariant property. The function in Equation (1) has some peculiar properties, such as an infinite number of periods in the range $0 \leq r < \varepsilon$, and the phase approaches $-\infty$ as the radius tends to zero. The undesired effects of these properties can be largely avoided by removal of a central region below a threshold radius. Fig. 1 shows a one-dimensional example of a simple oscillating homogeneous function having the form of Equation (1), for values $0.01 \leq x \leq 1$.

The homogeneity condition can also be viewed as a self-similarity criterion. Self-similar functions produce correlation magnitude peaks even when one of the correlated functions is rescaled. A complex function with the self-similarity property is:

$$f_{\alpha}(r) = r^p \exp[i\alpha \ln(r)] \quad (4)$$

A scale change provides:

$$f_{\alpha}(ar) = a^p r^p \exp[i\alpha \ln(r)] \exp[i\alpha \ln(a)] = a^p \exp[i\alpha \ln(a)] f_{\alpha}(r) \quad (5)$$

which introduces a magnitude and phase change. By using a complex exponent:

$$\exp[i\alpha \ln(r)] = r^{i\alpha} \quad (6)$$

Equation (4) can be written as:

$$f_{\alpha}(r) = r^{p+i\alpha} \quad (7)$$

Equation (7) represents a family of functions, which have a periodic radial structure. Figs. 2A and 2B show the real and imaginary parts of a pattern having the form of Equation (7) where a polar distance r is defined in terms of the Cartesian axes as $r^2 = x^2 + y^2$ and in which values of $r \leq R_1$ has been removed to avoid aliasing. The complex

function $f_\alpha(r)$ has negative values. Therefore, for the function $f_\alpha(r)$ to be displayed, the values the function $f_\alpha(r)$ have been normalised around a value of 127, with all values ranging from 0 to 255, with 0 representing black, 255 representing white, and intermediate levels representing levels of grey.

5 Functions of the form of Equation (7) have some useful orthogonality properties over an annular region, with the annular region defined by a maximum radius R_2 and the minimum radius R_1 . Consider the radial function:

$$f_m(r) = r^p r^{i\alpha_m} \quad (8)$$

10 The correlation at the origin, or zero shift, is defined by an overlap integral I_{mn} of this function $f_m(r)$ with another similar function $f_n(r)$ with parameter α_n instead of parameter α_m , and can be written in polar coordinates as:

$$I_{mn} = \int_{R_1}^{R_2} 2\pi r f_m(r) f_n^*(r) dr = \frac{2\pi \left(R_2^{2p+2} R_2^{i(\alpha_m - \alpha_n)} - R_1^{2p+2} R_1^{i(\alpha_m - \alpha_n)} \right)}{2p + 2 + i(\alpha_m - \alpha_n)} \quad (9)$$

From Equation (9), it can be seen that a prerequisite of orthogonality of the functions $f_m(r)$ and $f_n(r)$, is that $p = -1$. For one-dimensional functions, the orthogonality prerequisite is $p = -1/2$.

Generally, the magnitude squared of the overlap integral $|I_{mn}|^2$ may be written as a sinc function as follows:

$$|I_{mn}|^2 = \frac{(4\pi)^2 \sin^2 \left(\frac{1}{2} [\alpha_m - \alpha_n] \ln [R_2/R_1] \right)}{(\alpha_m - \alpha_n)^2} \quad (10)$$

20 The magnitude of the overlap integral $|I_{mn}|$ is a maximum as the parameters α_n and α_m approach $\alpha_n - \alpha_m = 0$, and zero when

$$\alpha_m - \alpha_n = \frac{2\pi j}{\ln[R_2/R_1]}, \quad j = \text{integer}, \text{ but } j \neq 0 \quad (11)$$

In practice, the magnitude of the overlap integral $|I_{mn}|$ is small or negligible when

$$|\alpha_m - \alpha_n| > \frac{2\pi}{\ln[R_2/R_1]} \quad (12)$$

The above condition is an approximate orthogonality condition, useful for
5 estimation purposes. In practice the ratio R_2/R_1 is chosen to be of the order 2 to 4, so that
 $\ln(R_2/R_1) \approx 1$.

By including a spiral phase function in Equation (8), thereby causing polar angle
 $\theta = \tan^{-1}\left[\frac{y}{x}\right]$ variations in the pattern function, it can be shown that the pattern function
retains its scale invariant and orthogonality properties. Consider a scale and rotation
10 invariant pattern g , which has a circular harmonic phase defined by the parameter k , where
parameter k is an integer. Such a function is sometimes referred to as a logarithmic radial
harmonic function [LRHF], and has the form:

$$g_{mk}(r, \theta) = r^p r^{i\alpha_m} e^{ik\theta} \quad (13)$$

The overlap integral I_{mknl} of this LRHF $g_{mk}(r, \theta)$ with another similar LRHF $g_{nl}(r, \theta)$
15 with parameters α_n and k , over an annular region, is:

$$I_{mknl} = \int_{-\pi}^{+\pi} \int_{R_1}^{R_2} 2\pi r g_{mk}(r) g_{nl}^*(r) dr d\theta = 2\pi \int_{-\pi}^{+\pi} e^{i(k-l)\theta} d\theta \int_{R_1}^{R_2} r^{2p+1} r^{i(\alpha_m - \alpha_n)} dr \quad (14)$$

As is evident from Equation (14), the overlap integral I_{mknl} is simple to calculate
because of the radial/tangential separability. Equation (14) can be further simplified
because the tangential component integrates to a Kronecker delta function as follows:

$$\int_{-\pi}^{\pi} e^{i(k-l)\theta} d\theta = 2\pi\delta_{kl} = \begin{cases} 2\pi & , k = l \\ 0 & , k \neq l \end{cases} \quad (15)$$

causing the overlap integral I_{mknl} to simplify to

$$I_{mknl} = (2\pi)^2 \delta_{kl} \frac{(R_2^{2p+2} R_2^{i(\alpha_m - \alpha_n)} - R_1^{2p+2} R_1^{i(\alpha_m - \alpha_n)})}{2p+2+i(\alpha_m - \alpha_n)} \quad (16)$$

Again, at orthogonality where $p=-1$, the magnitude squared of the overlap integral
5 is:

$$|I_{mknl}|^2 = (4\pi)^2 \delta_{kl} \frac{\sin^2\left(\frac{1}{2}[\alpha_m - \alpha_n] \ln[R_2/R_1]\right)}{(\alpha_m - \alpha_n)^2} \quad (17)$$

The preceding analysis refers to complex exponential functions, but in practice, images are limited to real, as well as positive, reflectivity, transmissivity, or intensity values. It can be shown that if the overlap integral I_{mknl} is calculated for the real part of
10 one LRHF g_{mk} with a full complex LRHF g_{nl} , a magnitude squared of the overlap integral $|I_{mknl}|^2$ would be obtained that is similar to Equation (17), but reduced by a factor of four.

Therefore, the LRHF g_{mk} is defined by the real value m and integer parameter k , where real value m defines in the parameter α_m as:

$$15 \quad \alpha_m = \frac{2\pi m}{\ln[R_2/R_1]} \quad (18)$$

In a typical application the LRHF g_{mk} is evaluated over a discrete image with a finite size, and where the pixel positions (x, y) only contain discrete integer values. To avoid aliasing, constraints are imposed on the allowable values for the parameters k and α_m .

The LRHF g_{mk} has a well defined local frequency $q(x,y)$, which is defined as the modulus of the gradient of the phase Ψ_{mk} of the LRHF $g_{mk}(r)$, so

$$q(x,y) = \sqrt{\left(\frac{\partial \Psi_{mk}}{\partial x}\right)^2 + \left(\frac{\partial \Psi_{mk}}{\partial y}\right)^2} \quad (19)$$

where

$$5 \quad g_{mk} = |g_{mk}| \exp(i\Psi_{mk}) \quad (20)$$

Hence, from Equation (13), the phase Ψ_{mk} is

$$\Psi_{mk} = \alpha_m \ln r + k\theta \quad (21)$$

$$\frac{\partial \Psi_{mk}}{\partial x} = \frac{\alpha_m}{r} \frac{dr}{dx} + k \frac{d\theta}{dx} = \frac{x\alpha_m - ky}{r^2} \quad (22)$$

$$\frac{\partial \Psi_{mk}}{\partial y} = \frac{\alpha_m}{r} \frac{dr}{dy} + k \frac{d\theta}{dy} = \frac{y\alpha_m + kx}{r^2} \quad (23)$$

10 Substituting Equations (22) and (23) into Equation (19), local frequency $q(x,y)$ is:

$$q(x,y) = \frac{\sqrt{\alpha_m^2 + k^2}}{r} \quad (24)$$

In other words, the radial and tangential frequencies are square additives. In fact the full 2D frequency is just the vector sum of the radial and tangential frequency vectors.

It is also noted that the orientation of the local frequency $q(x,y)$ is always fixed relative to

15 the polar angle θ :

$$\tan\left[\frac{\partial \Psi_{mk}}{\partial y} / \frac{\partial \Psi_{mk}}{\partial x}\right] = \tan\left[\frac{y\alpha_m + kx}{x\alpha_m - ky}\right] = \tan[\chi + \theta] \quad (25)$$

where

$$\tan[\chi] = \frac{k}{\alpha_m}, \tan[\theta] = \frac{y}{x} \quad (26)$$

This property means that spirals in the LRHF g_{mk} are equi-angular.

The minimum frequency q_{min} for an annular LRHF g_{mk} occurs at the maximum radius R_2 and the maximum frequency q_{max} at the minimum radius R_1 defined respectively

5 by:

$$q_{max} = \frac{\sqrt{\alpha_m^2 + k^2}}{R_1}, \quad q_{min} = \frac{\sqrt{\alpha_m^2 + k^2}}{R_2} \quad (27)$$

The maximum frequency q_{max} is kept below the Nyquist frequency of the discrete image. Figs. 3A and 3B show the real and imaginary parts respectively of a typical LRHF g_{mk} with parameters $k=50$ and $\alpha_m \approx 50$.

10 The foregoing described the basic properties of LRHFs. However, the property of most interest in this implementation is their correlation property. Correlation at the origin has been dealt with in the overlap integral $I_{mkl n}$.

In the more general case of cross-correlation and auto-correlation, a 2D-correlation function is obtained. An efficient method of correlating two large image functions is via
15 the Fast Fourier Transform (FFT).

It is convenient to work with continuous Fourier Transforms initially, although much of the mathematics transfers directly to the discrete case with discrete Fourier transforms, with the exception of infinite frequency parts. Consider first the case of purely radial functions with complex exponent c , having the form of Equation (8), and its
20 transform:

$$r^{-c} \Leftrightarrow q^{c-2} 2^{1-c} \frac{\Gamma(1-c/2)}{\Gamma(c/2)} \quad (28)$$

Here $\Gamma()$ is the generalised factorial (gamma) function. Using partial derivatives it can be shown that LRHFs g_{mk} having the form of Equation (13), have the following transform pair:

$$r^p r^{i\alpha_m} e^{ik\theta} \Leftrightarrow \mu_{mkp} q^{-p-2} q^{-i\alpha_m} e^{ik\phi} \quad (29)$$

5 The parameter μ is a complex constant related to the gamma function $\Gamma()$. It is noted that no coordinate scaling is necessary to estimate the form of the Fourier transform. In fact the Fourier phase ϕ is essentially the same as the spatial phase θ , except for a sign reversal in the radial component. This can be seen from the following:

$$\arg[r^p r^{i\alpha} e^{in\theta}] = \alpha \ln[r] + n\theta \quad (30)$$

$$10 \quad \arg[\mu_{mkp} q^{-p-2} q^{-i\alpha_m} e^{ik\phi}] = \text{const} - \alpha_m \ln[q] + k\phi \quad (31)$$

One of the principle applications of correlation in image processing is in the area of template matching. Correlation is therefore used to detect the presence of a pattern, such as a LRHF g_{mk} , in an image f , where the image $f(x,y)=p(x,y)+g_{nl}(x,y)$. Correlation between pattern g_{mk} and image f produces a 2 dimensional image with maximum values at
15 positions where the image f best matches the pattern g_{mk} . The Fourier correlation theorem provides:

$$h(x,y) = f(x,y) \otimes g(x,y) \Leftrightarrow F^*(u,v)G(u,v) = H(u,v) \quad (32)$$

Thus, correlation can be implemented by Fourier transforming the image f and the pattern g to obtain Fourier transformed functions F and G , complex conjugating one of
20 the Fourier transformed functions, say F , and then multiplying these two functions F^* and G , before transforming back.

It is also noted that:

$$\begin{aligned} h(x, y) &= [p(x, y) + g_{nl}(x, y)] \otimes g_{mk}(x, y) \\ &= [p(x, y) \otimes g_{mk}(x, y)] + [g_{mk}(x, y) \otimes g_{mk}(x, y)] \end{aligned} \quad (33)$$

Hence, the effectiveness of the embedding and detection of pattern g_{mk} in typical images depends on the cross-correlation of the original image p with the chosen pattern g_{mk} being of low magnitude and widely dispersed. This is difficult to estimate however, generally, the cross-correlation part is very small compared to the auto-correlation part. The heuristic argument for this is that LRHFs do not resemble features in typical images p . The LRHFs proposed have both wide spatial support and wide spectral support.

Consider the correlation between two LRHFs $g_{mk}(r)$ and $g_{nl}(r)$, being the second term in Equation (33). The Fourier transforms of the LRHFs $g_{mk}(r)$ and $g_{nl}(r)$ are of the form:

$$g_{mk}(r) = r^p r^{i\alpha_m} e^{ik\theta} \Leftrightarrow \mu_{mkp} q^{-p-2} q^{-i\alpha_m} e^{ik\phi} \quad (34)$$

$$g_{nl}(r) = r^p r^{i\alpha_n} e^{il\theta} \Leftrightarrow \mu_{nlp} q^{-p-2} q^{-i\alpha_n} e^{il\phi} \quad (35)$$

The product of the complex conjugate of the transform of LRHF $g_{mk}(r)$ and the transform of $g_{nl}(r)$, provides:

$$H_{mknl}(u, v) = \mu_{mkp} q^{-p-2} q^{+i\alpha_m} e^{-ik\phi} \mu_{nlp} q^{-p-2} q^{-i\alpha_n} e^{il\phi} = \mu_{mkp} \mu_{nlp} q^{-2p-4} q^{i(\alpha_m - \alpha_n)} e^{i(l-k)\phi} \quad (36)$$

The phases partly cancel when the two chosen LRHFs $g_{mk}(r)$ and $g_{nl}(r)$ are similar. Only when the functions are identical do the phases entirely cancel out. Phase cancellation is the classic condition for maximum correlation, although a purely linear phase component can exist and only indicates a shift in the two original functions.

In the case where the two LRHFs $g_{mk}(r)$ and $g_{nl}(r)$ are identical, Equation (36) reduces to:

$$H_{mkmk}(u, v) = (\mu_{mkp})^2 q^{-2p-4} \quad (37)$$

In such a case the correlation peak will be of the form

$$\left. \begin{aligned} h_{mkmk}(x, y) &\propto r^{2(p+1)}, & p \neq -1 \\ h_{mkmk}(x, y) &\propto \delta(x, y), & p = -1 \end{aligned} \right\} \quad (38)$$

The above equations are ideals, and the correlation peaks will be finite and
5 discrete approximations to the ideal in practice.

However, the pattern $g_{nl}(x, y)$ is typically limited to real values only when embedding in the discrete image $f(x, y) = p(x, y) + g_{nl}(x, y)$. The discrete image $f(x, y)$ is typically further limited by only 8 bits of data per pixel, thus greyscale levels 0-255. As noted earlier, all the preceding analysis extends easily to the case where a real pattern
10 $\Re(g_{mk})$ is embedded in an image $p(x, y)$ and detected with a complex pattern g_{nl} . The main difference is a 2 times increase in the noise compared to the full complex correlation, or:

$$|\Re(g_{mk}) \otimes g_{nl}| \approx \frac{|g_{mk} \otimes g_{nl}|}{2} \quad (39)$$

Another difference is that the correlation of a pattern g_{nl} with the real part of that pattern g_{nl} is no longer a real power of r . Some oscillating structure will "leak" through,
15 both radial and tangential.

The underlying mathematical method of LHRF correlation is invariant to any scale variation. As noted before, the maximum frequency q_{max} is kept below the Nyquist frequency of the discrete image. The maximum frequency q_{max} is as defined in Equation (27), and determines the size of the 'hole' in the centre of the pattern. Similarly the size
20 of the image introduces a maximum pattern size. In the simplest case, the pattern is

restricted to an annular region defined by radii R_1 and R_2 . However, square or other shapes may also be used to restrict the patterns.

In addition to the conventional correlation process outlined above, and in particular Equations (36), (37) and (38), enhanced forms of correlation may also be
5 usefully employed for the detection of embedded patterns.

One form of enhanced correlation is to boost the high frequency components of the conventional correlation. This has the effect of changing the real exponent p in Equations (37) and (38) resulting in a correlation peak which resembles the delta function in the second part of Equation (38).

10 Another form of enhanced correlation is known as "phase-only" correlation. Phase only correlation is implemented by taking the Fourier correlation magnitude, expressed in Equation (37) for example, and setting it to unity. This ensures that only the phase terms contribute to the overall correlation peak. Again, the peak shape tends to resemble a delta function.

15 A variety of enhanced correlation processes, which consist of intermediates between frequency-boosted correlation and phase-only correlation, are also possible and applicable to the correlation detection.

Roughly speaking, the ratio of the two radii R_1 and R_2 in the annulus determine the extremes of the possible scale variations before correlations fail completely. Hence, the
20 minimum scaling factor is R_1/R_2 and the maximum is R_2/R_1 . Preferably, the limits are set at 50% overlap area between an embedded pattern g_{km} and a detection pattern g_{ln} , in which case the two scaling ratios are:

$$\sqrt{\frac{1}{2}}\sqrt{1+\frac{1}{2\lambda^2}} \quad \text{and} \quad \sqrt{\frac{1}{2}}\sqrt{1+\frac{\lambda^2}{2}} \quad \text{where} \quad \lambda = \frac{R_1}{R_2} \quad (40)$$

The range factor in this case is

$$\lambda \sqrt{\frac{2 + \lambda^2}{1 + 2\lambda^2}} \quad (41)$$

In a typical case, for example, where $\lambda = 4$, then the ratios are 0.72 and 2.12.

The range of scale variation may be extended by performing the correlation upon a
5 number of differently scaled versions of the watermarked image. This allows the overlap
area to be improved in at least one of the correlations. So, for example a sequence of
images rescaled by progressive factors of 2 would guarantee one of the images to fit the
50% overlap criterion (for $\lambda \geq 4$), and hence give a strong correlation peak.

The foregoing described the properties of LRHFs. Fig. 4 shows a schematic
10 diagram of a process 450 of watermarking an image 400 or document with a pattern 410,
such as the real part of a LRHF g_{mk} shown in Fig. 3A. The pattern 410, which may be
called a watermark, is simply added to the image 400 to form a watermarked image 420.
If the image 400 is in colour, then the pattern 410 is added to the luminance part of a
colour image 400. This allows the watermark to survive when the watermarked image is
15 converted from colour to a greyscale representation.

Preferably, the pattern 410 component in the watermarked image 420 is invisible
or imperceptible to the human visual system under normal viewing conditions. This is
done by multiplying the pattern 410 with a constant embedded factor 430, thereby adding
a low intensity copy of the pattern 410 to the image 400.

20 A collection of patterns may also be added to the image 400. Fig. 5 shows the
sum of 6 shifted LRHFs, similar in form as those shown in Fig. 3A. Before patterns are
added to images for watermarking, a scale is applied to their intensity, or the intensity of
their sum in the case of a collection of patterns, so that their intensity is approximately of

the range -5 to +5 (for example) to avoid wide intensity variation. It is noted that the intensities of the image shown in Fig. 5 has been amplified to the range 0-255 to more clearly show the patterns.

Fig. 6 shows the watermarked image formed by adding the watermark represented in Fig. 5 to a test image, in this case Lena. The watermark is perceptible in regions having low intensity variation, such as region 501.

In a preferred implementation, an adaptive scheme is used to reduce the level of the watermark in regions having low intensity variation and increase the level of the watermark in regions of high intensity variance. The watermark is a real function with the following general form:

$$\hat{g}_{k,m,n}(x,y) = \Re\{g(r,\theta)\} = \Re\{w_n(r,\theta)r^p r^{i\alpha_m} e^{ik\theta}\} \quad (42)$$

The window function $w_n(r,\theta)$ is a slowly varying function relatively to the pattern function $r^p r^{i\alpha_m} e^{ik\theta}$. Firstly, the window function $w_n(r,\theta)$ is used to remove or de-emphasise the high frequency central region of the pattern function $r^p r^{i\alpha_m} e^{ik\theta}$. Furthermore, the window function $w_n(r,\theta)$ is also used to reduce the pattern intensity in regions of an image to which it is applied, where the pattern would otherwise be highly visible, such as "flat" sky regions. The de-emphasis window function $w_n(r,\theta)$ may be calculated by estimating the perceptual masking in various regions of the image. An example measure of perceptual masking is local gradient magnitude of the luminance in the image. Others include second partial derivatives of the luminance; local estimates of the "energy" or frequency content, local variance, and more sophisticated estimates of human visual system masking.

Fig. 7A shows a schematic diagram of an alternative process 750 of watermarking an image 700. A perceptual mask 720 is formed from the image 700. The pattern 710 with parameters k and m (or a combination of patterns) is then de-emphasised with the perceptual mask 720 by multiplying the pixel values of the perceptual mask 720 with
5 corresponding pixel values of the pattern 710. The resulting pattern is of the form of Equation (44). This de-emphasised pattern is added to the image 700 to form a watermarked image 730.

Preferably, the pattern 710 component in the watermarked image 730 is invisible or imperceptible to the human visual system under normal viewing conditions. This is
10 done by multiplying the pattern 710 with a constant embedded factor 740, thereby adding a low intensity copy of the pattern 710 to the image 700.

Fig. 7B shows the watermarked image formed by adding the watermark represented in Fig. 5 to the test image, using the process 750 shown in Fig. 7A. The watermark that was perceptible in region 501 of Fig. 6 is no longer perceptible in a
15 corresponding region 502.

The window function $w_n(r, \theta)$ can also contain other information, for example a constant phase (ie complex) factor. Such a phase factor causes a constant phase offset to the pattern function $r^p r^{i\alpha_m} e^{ik\theta}$. In one implementation, this phase factor is made random, making every watermark unique, even when the same parameters α_m and k are used. Such
20 a watermark would be even harder to detect.

Again, with colour images, the de-emphasised pattern $\hat{g}_{k,m,n}(x, y)$ may be added to the luminance part of the signal. Alternatively, the de-emphasised pattern $\hat{g}_{k,m,n}(x, y)$

may be added to the R, G, B, H, V, S, u, v etc channels of the colour image, or any combination thereof.

The watermark that is embedded into an image generally consists of a summation of separate basis patterns \hat{g} with varying location, windows, and tuning parameters:

$$5 \quad \sum_{n=1}^N w'_n(x-x_n, y-y_n) \cdot \hat{g}_{k(n),m(n),n}(x-x_n, y-y_n) \quad (43)$$

where window function w'_n removes or de-emphasises the high frequency central region of each of the separate basis patterns \hat{g} .

The window function $w(x,y)$ for applying perceptual de-emphasis may be applied after the summation process, to form a watermark as follows:

$$10 \quad w(x,y) \sum_{n=1}^N w'_n(x-x_n, y-y_n) \cdot \hat{g}_{k(n),m(n),n}(x-x_n, y-y_n) \quad (44)$$

The watermark encodes information in the centre location (x_n, y_n) strength, relative phase, and parameters $k(n)$ and $\alpha_{m(n)}$ of each of the N basis patterns \hat{g} . In practice the centre location (x_n, y_n) strength is not a robust carrier of information, as it can be easily attenuated, even accidentally, by any processing of the watermarked image.

15 Fig. 8 shows a schematic diagram of a process 800 of detecting a watermark in a watermarked image 810. The watermarked image 810 is simply correlated with a complex pattern 820 having parameters k and α_m , such as that shown in Figs. 3A and 3B, to form a result image 830. Referring to Equation (33), if the complex pattern 820 is present in the watermarked image 810, in particular the real part of a LRHF having
20 parameters k and α_m , then the result image 830 will have correlation magnitude peak(s) at centre location(s) where that pattern 820 was embedded into the image. The use of

different parameters, say l and α_n , in the pattern 820 will result in no correlation magnitude peaks in the result image 830.

With more than one basis pattern \hat{g} used in the watermark, the process 800 of detection may be repeated for each of the basis patterns \hat{g} .

5 The process 800 may also be used with watermarked images 810 where process 750 shown in Fig. 7A was used to embed the watermark 710 into the image 700, using de-emphasis of the watermark.

Fig. 9 shows a schematic diagram of an alternative process 900 of detecting a watermark in a watermarked image 910. A perceptual mask 920 is formed from the
10 watermarked image 910. The watermarked image 910 is then emphasised with the perceptual mask 920 by dividing the pixel values of the watermarked image 910 by pixel values of corresponding pixel values of the perceptual mask 920. This emphasised image 930 is correlated with the complex pattern 940 to for a result image 950.

Fig. 10A shows the magnitude image of the correlation of the correct LRHF
15 $g_{mk}(r)$ with the watermarked image of Fig. 6 using process 800. Fig. 10B shows the detail of the peak structure of one of the magnitude peaks of Fig. 10A. Fig. 11A shows the magnitude image of the correlation of the correct LRHF $g_{mk}(r)$ with the watermarked image of Fig. 7B using process 900, whereas Fig. 11B shows the detail of the peak structure of one of the magnitude peaks of Fig. 11A. Note that the magnitude peaks
20 shown in Figs. 10B and 11B are very sharp and clear, whereas the background correlation is small. An improvement in the sharpness of the magnitude peaks is also visible in Fig. 11B. Thus, whereas the watermark process 750 using de-emphasis makes the pattern less

perceptible, the watermark detection process 900 using emphasis improves detection by resulting in sharper magnitude peaks.

The magnitude peaks can only be detected by correlation with the known LRHF(s) used for embedding, or by an exhaustive search of correlation magnitude peaks by using
5 the full range of parameters k and α_m . The exhaustive search can be expected to be many orders of magnitude slower than detection using the correct parameters k and α_m , making the method difficult to attack.

Fig. 12 shows the watermarked image of Fig. 7B rotated by 20 degrees and increased in size by 20%. The image has also been cropped and a gamma correction
10 power of 0.8 has been applied. These operations were performed on the 8-bit image data using linear interpolation.

Performing the watermark detection process 900 shown in Fig. 9, using the correct detection LRHF $g_{mk}(r)$, the result shown in Fig. 13 is obtained. Fig. 14 shows the detail of the peak structure of one of the magnitude peaks of Fig. 13. There is some degradation
15 of the peak structure compared to the magnitude peaks of Fig. 11B, but the correlation magnitude peaks are still well above the background noise level.

For an image containing a single magnitude peak, detection is relatively straightforward, in that the pixel containing the maximum modulus value is selected, and its coordinates define the centre of the embedded pattern.

20 For images containing multiple peaks to be detected, a slightly more complex approach is used. If a detection image contains s peaks, those s peaks may be detected as follows:

- Find the pixel with maximum modulus among pixels in consideration. This pixel p_i is one of the s pixels;
- Exclude all pixels in a disk of some radius q around pixel p_i from consideration; and
- 5 - Repeat s times in total.

The radius q is chosen depending upon the application. When alignment peaks are very well spaced, a large value for q , say 20 pixels, may be used. Peaks used to encode information may be much closer together, and a smaller value for q should be used.

10 The proposed processes of watermarking and detection of watermarks are inherently robust to most image distortions. These include:

- Scale change from about 50% to +200%;
- Any rotation;
- JPEG compression down to about a 10:1 compression;
- 15 Gamma correction; and
- Low pass filtering.

In addition to the above, the method is more difficult to defeat than known methods where the watermarks can be detected by analysing the Fourier magnitudes of an image. Detection of LRHF $g_{mk}(r)$ based watermarks requires many correlations, typically more than 1000, if the parameters α_m and k of the LRHF $g_{mk}(r)$ are unknown.

20

There are many applications in machine and computer vision that require registration and alignment of objects. Accordingly, in a further implementation, LRHFs can be used purely to embed reference marks in images to allow reliable registration and

alignment of an image of, or applied to the object. The LRHFs may be embedded visibly or invisibly. Additional patterns may be added to carry a watermark message.

The detection of the pattern is performed by using method 800 or 900, shown in Figs. 8 and 9 respectively. Once the registration marks in the form of magnitude peaks in the resulting magnitude image are detected then the rotation and scaling parameters can be estimated and the watermarked image set back to its nominal scale and rotation setting.

An example registration method is outlined as follows:

For encoding, peaks are encoded at three corners of a square of known size.

For decoding, these peaks are detected in a possibly transformed image. The rotation angle may be estimated using the vector between the two peaks which are furthest apart. Similarly, the total scaling factor may be estimated using the distance between these two peaks. The shear factor may be estimated by measuring how far the angle between the three points differs from the perpendicular. The change in aspect ratio may be estimated by measuring the difference in the length of the horizontal side and the vertical side.

The four parameters (angle, scaling, shear and aspect ratio) completely define a linear transformation. This transformation may be inverted to restore the image to its original size and orientation.

Scaling and rotation may be performed by a variety of resampling algorithms. Typically a high quality resampling using bi-cubic interpolation, Fourier interpolation, or even a non-linear resampling scheme may be used. Once the watermarked image is back at its nominal settings, an alternative watermarking or steganographic method may be utilised to extract further information from the image.

In another implementation, the registration patterns are used in conjunction with any other watermarking technique. The registration is performed before reading the embedded watermark.

Registration may include focusing because the correlation magnitude peaks provide a nice smooth variation in magnitude with respect to changes in the focus of imaging systems. Focus can be estimated by correlation peak width. An advantage of a width based measure of focus is that it is normalised and does not depend upon the absolute peak level.

Registration may further include aspect ratio correction and shearing to some extent, due to the strength of the correlation magnitude peaks.

The above patterns used as the watermark were all radial-tangential functions having the form of Equation (40). However, patterns that only vary in one dimension may also be used, such as patterns of the following form:

$$g_m(x, y) = \Re \left\{ w(x, y) |x|^{i\alpha_m} \right\} \quad (45)$$

This pattern only has variation in a x direction. Any direction could be chosen in practice. Process 450 or 750, shown in Fig. 4 and 7 respectively, may be used to embed the pattern into an image.

The one dimensional pattern may be detected using process 800 or 900, shown in Figs. 8 and 9 respectively, to detect the centre line position of a pattern, if the correct parameter α_m is known. In particular, a two-dimensional complex pattern having the form of Equation (13) is used as the pattern 820 in process 800, with the two-dimensional complex pattern having the same parameter α_m , but zero spiral parameter k . The detection is unaffected by shear or anamorphic magnifications.

It is also possible to construct scale invariant patterns from a separable product of one dimensional patterns, thus having the form:

$$s_{l,m}(x,y) = w(x,y) |x'|^{i\alpha_l + p_x} |y'|^{i\alpha_m + p_y} \quad (46)$$

However, such patterns are not rotation invariant. It is noted that the separable
5 directions (x', y') do not need to be orthogonal. A sequence of the above patterns may be summed to form the overall watermark. Radial harmonic patterns of the form of Equation (40) may also be added. In one implementation, the radial harmonic pattern(s) is added for registration, allowing the watermarked image to be rotated back to its original orientation, before the pattern is detected by using one of the detection processes 800 or
10 900.

As stated above, the watermark encodes information in the centre location (x_n, y_n) strength, phase, and parameters $k(n)$ and $\alpha_{m(n)}$ of each of the N basis patterns \hat{g} . For example, the location (x_n, y_n) of each peak could store several bits of data. More sophisticated methods may also be used such as described below. Detection of the stored
15 data requires that the peak and its position be identified reliably. This process may entail some error correcting or data redundancy scheme.

Using the peak localisation property, several independent watermarking basis patterns \hat{g} , with each basis pattern \hat{g} centred on a pixel in a 64x64 square grid in the image which is used for watermarking. To allow accurate extraction, each grid position is
20 preferably separated by 7 pixels, thus the template grid pattern covers a region of 448x448 pixels in the candidate image, which is small enough to embed in all but the smallest images.

Because the detection error is usually small and typically within 1-2 pixels, a scaling factor of 50% would result in a grid spacing of 3.5 pixels, which is still reliably detectable. Any scaling to smaller dimensions could result in errors during message decoding. Scaling to increased image size could tend to enhance the reliability of
5 detection.

This technique uses three points on a regular grid to provide information on the pattern orientation and scaling, a point to encode image length, and subsequent points to encode bits of information.

Once the embedding grid has been established, each row and column position of
10 the marks in the original grid may be derived from the detected position of each basis embedded in the watermarked image.

The first three points define the corners of the embedding grid. A different basis pattern \hat{g} defines each point, thus they may be detected in order and their relative positions used to establish the orientation and scaling of the grid in the watermarked
15 image, and sufficiently small shear or anamorphic scaling changes.

From the three corners of the grid, a linear transformation may be derived from the coordinates of the watermarked image to that of the original 64 point by 64 point grid.

The fourth point in the sequence of detected bases is used to encode the length of the encoded message in bits. By assigning numbers from 0 to 4095 to each grid position,
20 the fourth point may indicate a message of any length from 0 to 4095 bits.

Subsequent points encode the bits of the message by concatenating the bits representing the row and column address of each point. In a 64 point by 64 point grid, each row or column address codes exactly 64 (2^6) separate values. Hence, each point on the 64x64 grid encodes up to 12 bits.

Modifications to this simple technique provide encoding schemes with slightly different properties.

By embedding patterns on a 64 point by 64 point grid with only a single basis pattern \hat{g} and B points, messages of $\lfloor \log_2 \left({}^{4096}C_{(B-3)} \right) \rfloor$ bits using three alignment points
5 may be stored, where C is the binomial coefficient and $\lfloor \cdot \rfloor$ is the floor operator. There are two advantages of this technique. Firstly, only a single correlation need be performed during detection, thus providing a faster detection method. Secondly, any image transformation will affect the relative phase of all detected points similarly. This provides an opportunity to encode at least one extra bit of information per basis, by comparing the
10 complex phase of each detected peak with that of the first.

Encryption may be performed on the bitstream to hide information from persons not holding the appropriate keys.

Checksums may be added to the bitstream to provide verification of the detected watermark, and also as an aid in locating information-containing watermark patterns.

15 Error-correcting codes may be added to the bitstream to increase the robustness of the encoded bitstream, albeit with the requirement of embedding more basis patterns \hat{g} in the original watermark, perhaps making the mark more visible.

To make the embedded pattern harder to discover with malicious intent, multiple basis patterns \hat{g} may be added together at the same position and the sum of their
20 detection magnitude peaks used during detection. In this case, each detection peak alone may be too small to measure, but the summation of the amplitude of all detection images will combine to produce a very well-defined peak. Only by knowing a large fraction of the multiple bases can the detection peak, and hence the basis for watermarking, be found.

The process of embedding and detecting rotation and scale invariant bases has several properties, which provide the means to embed a substantial amount of information in an image watermark and recover it with great reliability. These properties include:

5 The amplitude peaks recovered from a watermarked image are extremely sharp and well localized, typically within 1-2 pixels. Thus their embedded position in the original image can be recovered with a great degree of accuracy.

Each watermarking basis pattern \hat{g} is orthogonal to all other bases having different parameters k and α_m . Thus, if many different bases patterns \hat{g} are used in the watermark, a peak for each basis may be recovered almost independently of all other
10 bases patterns \hat{g} .

If a single basis pattern \hat{g} is used to embed a watermark, the magnitude peaks in the detected image will all be of identical complex phase. If multiple basis patterns \hat{g} are used which differ only in complex phase, i.e. each basis pattern \hat{g} is multiplied by a different complex constant of unit modulus, then the relative phase of all detected
15 magnitude peaks will be preserved. In the best case, a single detected point may be used to determine the base phase, and the phase of subsequent magnitude peaks in the result image will retain their relative relationship to this base point.

The sharpness and amplitude of detection magnitude peaks is not substantially affected by any rotation or scaling transformations applied to the image, although the
20 position of the magnitude peaks themselves will be rotated and scaled with the watermarked image. Thus, any rotation or scaling can be detected and corrected for by using the position of alignment points.

To a certain extent, shearing or anamorphic (aspect ratio) changes may also be detected and taken into account, thus the method is applicable to arbitrary linear transformations as long as the shear, scaling or anamorphic component is small enough.

By using iterative searching, any linear transformation to the coordinate system of
5 a watermarked image that did not ruin its content could be detected and corrected for.

In addition to the aforementioned uses for embedded patterns, there are numerous other applications, some of which will now mentioned.

The use of a watermark allows a code to be embedded into an image. Such a code will remain with the image even if the header and other metadata of the image file are
10 removed. This allows the code to remain strongly attached to the actual image itself. The code may be usefully employed to define the address or location of the original metadata related to the image. The metadata may contain owner identification, camera settings, geographical location, details of the subjects in the image, or any number of pieces of other information. Image metadata may be stored on the same device as the image, or on
15 a server connected by a network, or even a server owned by a third party on the Internet.

A watermark can also embed a copyright owner's information into an image. The copyright information will be difficult to detect or remove by anyone who does not have knowledge of the parameters used to define the embedded patterns. Without the embedded pattern parameters it is necessary to search a large number of possible
20 configurations before correlation peaks may be detected. The difficulty in searching may be sufficient to dissuade attacks upon this copyright marking method.

The processes 450, 750, 800 and 900 can be implemented on a system 200 shown in Fig. 15. In particular, one or more of the processes 450, 750, 800 and 900 may be implemented as software executing within the system 200, where the processes 450, 750,

800 and 900 are effected by instructions in the software that are carried out by the system 200. The software may be stored in a computer readable medium, including the storage devices described below, for example. The software is loaded into the system 200 from the computer readable medium, and then executed by the system 200. A computer
5 readable medium having such software or computer program recorded on it is a computer program product. The use of the computer program product in the system 200 preferably effects an advantageous apparatus for watermarking, watermark detection or registration.

The pattern embedding and detecting processes 450, 750, 800 and 900 may be included as a plug-in module for commercially available software packages. In particular,
10 packages which are used for the manipulation and editing of digital image files would benefit by the addition of the pattern embedding and detection software.

The embedding and/or the detection of the watermarks may be operated as a service by a third party. The images may be conveyed by a digital network for embedding and then returned to the owner with the hidden mark. Similarly an image thought to
15 contain a mark may be submitted to the third party operator for detection of marks with specified parameters.

Libraries of digital images could incorporate embedded patterns to maintain connections with image metadata and also to maintain image copyright information.

Digital cameras, whether still or video would benefit from the inclusion of pattern
20 embedding software and/or software to allow embedding of information immediately following image acquisition. The advantage in such a system is that unmarked images would be difficult or impossible to obtain.

The system 200 may, for example, be a general-purpose computer, a digital camera, a video camera, a scanner or a photocopier. The system 200 comprises a

computer module 201, output device(s) 215 and input devices such as controls 202 and digital capture device 203. The digital capture device 203 may be an image sensor, such a two-dimensional CCD array. The computer module 201 typically includes at least one processor unit 205, a memory unit 206, for example formed from semiconductor random access memory (RAM) and read only memory (ROM), input/output (I/O) interface(s) and a storage device 209. The components 205 to 213 of the computer module 201, typically communicate via an interconnected bus 204 and in a manner which results in a conventional mode of operation of the computer system 200 known to those in the relevant art

10 In the case where the system 200 is a general-purpose computer, the output device 215 includes a display device. A printer may also be provided. The controls 202 include a keyboard and a mouse. The storage device 209 typically includes a hard disk drive, a floppy disk drive and a CD-ROM drive. Typically, the application program is resident on the storage device 209, and read and controlled in its execution by the processor 205.

15 Intermediate storage of the program may be accomplished using the semiconductor memory 206, possibly in concert with the storage device 209. In some instances, the application program may be supplied to the user encoded on a CD-ROM or floppy disk and read via a CD-ROM drive or floppy disk drive 211, or alternatively may be read by the user from a network (not illustrated). Still further, the software can also be loaded

20 into the computer system 200 from other computer readable medium including magnetic tape, a ROM or integrated circuit, a magneto-optical disk, a radio or infra-red transmission channel between the computer module 201 and another device, a computer readable card such as a PCMCIA card, and the Internet and Intranets including e-mail transmissions and information recorded on websites and the like. The foregoing is merely

exemplary of relevant computer readable mediums. Other computer readable mediums may be practiced without departing from the scope and spirit of the invention. In the case where the system 200 is a digital camera or video camera, the image(s) and/or the watermarked image(s) may be stored onto the storage device 209 or communicated to
5 another device (not illustrated).

One or more of the processes 450, 750, 800 and 900 may alternatively be implemented in dedicated hardware such as one or more integrated circuits performing the functions or sub functions of those processes 450, 750, 800 and 900. Such dedicated hardware may include graphic processors, digital signal processors, or one or more
10 microprocessors and associated memories.

Thus, images may be obtained by the system 200 using the digital capture device(s) 202 or through the storage device 209. Watermarked images may be displayed, printed, stored or communicated to other devices. Similarly, watermarked images may be obtained by the system 200 using the digital capture device(s) 202 or through the storage
15 device 209.

In another implementation, the digital capture device 203 is an audio device, and the system 200 is used to embed watermarks of the form:

$$g_m(t) = |t|^{i\alpha_m + p} \quad (47)$$

into audio streams, where t is a time in the audio stream.

20 Audio signals whether digital or (high quality) analogue may have very low level patterns or signals added with very little differences being perceptible. If the signal length is long enough, then a strong correlation peak is obtainable provided the pattern parameters are known. In this way information (copyright or otherwise) may be

embedded in the audio signal. The embedding device, which may be software or hardware, may be located near the input of an audio capture device, such as a microphone. Alternatively the embedding process may take place near the output device of an audio production system. In this case the embedded patterns would be optimised for the final
5 output medium, such as Compact Disc or Digital Audio Tape. The patterns would survive and still be detectable after sophisticated watermark attacks such as pitch changing and resampling because of the scale invariant property.

In yet another implementation, the correlation is performed optically through the use of spatial light modulators.

10 The foregoing describes only some implementations, and modifications and/or changes can be made thereto without departing from the scope and spirit of the invention, the implementation(s) being illustrative and not restrictive.

In the context of this specification, the word “comprising” means “including principally but not necessarily solely” or “having” or “including” and not “consisting only
15 of”. Variations of the word comprising, such as “comprise” and “comprises” have corresponding meanings.

~~Claims~~ The Claims defining the invention are as follows:

1. A method of watermarking an image, said method comprising the step of:
mathematically adding at least one basis pattern to said image, wherein said basis
5 pattern(s) is scale and rotation invariant within a complex multiplicative constant.

2. A method as claimed in claim 1, wherein said basis pattern(s) is of the form:

$$g_{mk}(r, \theta) = r^{i\alpha_m + p} e^{ik\theta},$$

with k, p and α_m being parameters of said basic pattern(s), r being a polar distance defined
10 in terms of the Cartesian axes of said image as $r^2 = x^2 + y^2$ and $\theta = \tan^{-1} \left[\frac{y}{x} \right]$.

3. A method as claimed in claim 2 comprising the further initial step of removing
region(s) of said basis pattern(s) having frequencies above a predetermined frequency.

- 15 4. A method as claimed in claim 2 or 3, wherein at least a first and a second basis
patterns are added to said image, with at least one parameter k or α_m of said first basis
pattern being different to that of said second basis pattern.

5. A method as claimed in any one of claims 2 to 4, wherein a plurality of basis
20 patterns are added with different offset relative to a center of said image.

6. A method as claimed in any one of claims 2 to 5, comprising the further initial step of encoding information into at least one of said parameters, said offset, an amplitude or a relative phase added to said basis pattern.
- 5 7. A method as claimed in any one of claims 2 to 6, wherein parameter $k=0$ and said polar distance r is a function of Cartesian co-ordinate x or y only.
8. A method as claimed in any one of claims 1 to 7, comprising the further step of de-emphasising regions of said basis pattern(s) corresponding with regions of said image
- 10 having low intensity variation.
9. A method of detecting a pattern in a watermark of an image, said watermark comprising at least one basis pattern, with said pattern and said basis pattern(s) being scale and rotation invariant within a complex multiplicative constant, said method
- 15 comprising the steps of:
- correlating said image with said pattern; and
- locating one or more magnitude peaks, said peak(s) corresponding to center position(s) of basis pattern(s) having the same parameters as that of said pattern.
- 20 10. A method as claimed in claim 9, said pattern and said basis pattern(s) being of the form:

$$g_{mk}(r, \theta) = r^{i\alpha_m + p} e^{ik\theta},$$

with k , p and α_m being parameters of said pattern and basic pattern(s), r being a polar distance defined in terms of the Cartesian axes of said image as $r^2 = x^2 + y^2$ and $\theta = \tan^{-1} \left[\frac{y}{x} \right]$.

5 11. A method as claimed in claim 10 comprising the further initial step of removing regions of said pattern having frequencies above a predetermined frequency.

12. A method as claimed in claim 10 or 11, comprising the further final step of decoding information from at least one of said parameters, said peak position(s), an
10 amplitude or relative phase of said peak(s).

13. A method as claimed in any one of claims 9 to 12, comprising the further step of de-emphasising regions of said pattern corresponding with regions of said image having low intensity variation.
15

14. A method of adding registration marks to an image, said method comprising the step of:
mathematically adding a plurality of basis patterns to said image, wherein at least two of said basis patterns are added with different offsets relative to a center of said
20 image, and said basis patterns are scale and rotation invariant within a complex multiplicative constant.

15. A method as claimed in claim 14 wherein said basis patterns are of the form:

$$g_{mk}(r, \theta) = r^{i\alpha_m + p} e^{ik\theta},$$

with k , p and α_m being parameters of said basic patterns, r being a polar distance defined in terms of the Cartesian axes of said image as $r^2 = x^2 + y^2$ and $\theta = \tan^{-1} \left[\frac{y}{x} \right]$.

5 16. A method as claimed in claim 15, wherein at least one parameter k or α_m of a first basis pattern is different to that of a second basis pattern.

17. A method as claimed in any one of claims 14 to 16, comprising the further step of de-emphasising regions of said basis patterns corresponding with regions of said image
10 having low intensity variation.

18. A method of registering an image having a watermark embedded, said watermark comprising a plurality of basis patterns, said method comprising the steps of:

correlating said image with a pattern; said pattern and said basis patterns being
15 scale and rotation invariant within a complex multiplicative constant;

locating peak positions, said peak positions corresponding to center positions of basis patterns having the same parameters as that of said pattern;

comparing said peak positions with predetermined positions from an original image; and

20 transforming said image to invert linear transformations.

19. A method as claimed in claim 18 wherein said pattern and said basis patterns are of the form:

$$g_{mk}(r, \theta) = r^{i\alpha_m + p} e^{ik\theta},$$

with k and α_m being parameters of said pattern and basic patterns, r being a polar distance defined in terms of the Cartesian axes of said image as $r^2 = x^2 + y^2$ and $\theta = \tan^{-1} \left[\frac{y}{x} \right]$.

5 20. A method as claimed in claim 19 comprising the further initial step of removing regions of said pattern having frequencies above a predetermined frequency.

21. A method as claimed in any one of claims 18 to 20, comprising the further step of
10 de-emphasising regions of said pattern corresponding with regions of said image having low intensity variation.

22. A method of watermarking an audio stream, said method comprising the step of:
mathematically adding at least one basis signal to said audio stream, wherein said
basis signal(s) is scale invariant within a complex multiplicative constant.

15

23. A method as claimed in claim 22, wherein said basis signal(s) is of the form:

$$g_m(t) = |t|^{i\alpha_m + p},$$

with α_m and p being parameters of said basic signal(s) and t being a time in said audio stream.

20

24. A method as claimed in claim 23 comprising the further initial step of removing region(s) of said basis signal(s) having frequencies above a predetermined frequency.

25. A method as claimed in any one of claims 22 to 24, comprising the further step of de-emphasising regions of said basis signal(s) corresponding with regions of said audio stream having low amplitude variation.

5 26. A method of detecting a signal in a watermark of an audio stream, said watermark comprising at least one basis signal, with said signal and said basis signal(s) being scale invariant within a complex multiplicative constant, said method comprising the steps of:
correlating said audio stream with said signal; and
locating one or more magnitude peaks, said peak(s) corresponding to center
10 position(s) of basis signal(s) having the same parameter as that of said signal.

27. A method as claimed in claim 26 wherein said signal and said basis signal(s) are of the form:

$$g_m(t) = |t|^{i\alpha_m + p},$$

15 with α_m and p being parameters of said signal and basic signal(s) and t being a time in said audio stream

28. A method as claimed in claim 27 comprising the further initial step of removing regions of said signal having frequencies above a predetermined frequency.

20

29. A method as claimed in any one of claims 26 to 28, comprising the further step of de-emphasising regions of said signal corresponding with regions of said audio stream having low intensity variation.

30. Apparatus for watermarking an image, said apparatus comprising:

means for mathematically adding at least one basis pattern to said image, wherein said basis pattern(s) is scale and rotation invariant within a complex multiplicative
5 constant.

31. Apparatus as claimed in claim 30, wherein said basis pattern(s) is of the form:

$$g_{mk}(r, \theta) = r^{i\alpha_m + p} e^{ik\theta},$$

with k , p and α_m being parameters of said basic pattern(s), r being a polar distance defined
10 in terms of the Cartesian axes of said image as $r^2 = x^2 + y^2$ and $\theta = \tan^{-1} \left[\frac{y}{x} \right]$.

32. Apparatus as claimed in claim 31, further comprising means for removing region(s) of said basis pattern(s) having frequencies above a predetermined frequency.

15 33. Apparatus as claimed in claim 31 or 32, wherein at least a first and a second basis patterns are added to said image, with at least one parameter k or α_m of said first basis pattern being different to that of said second basis pattern.

20 34. Apparatus as claimed in any one of claims 31 to 33, further comprising means for encoding information into at least one of said parameters, said offset, an amplitude or a relative phase added to said basis pattern.

35. Apparatus as claimed in any one of claims 31 to 34, wherein parameter $k=0$ and said polar distance r is a function of Cartesian co-ordinate x or y only.

36. Apparatus as claimed in any one of claims 30 to 35, wherein a plurality of basis
5 patterns are added with different offset relative to a center of said image.

37. Apparatus as claimed in claim 30 or 36, further comprising means for de-emphasising regions of said basis pattern(s) corresponding with regions of said image having low intensity variation.

10

38. Apparatus for detecting a pattern in a watermark of an image, said watermark comprising at least one basis pattern, with said pattern and said basis pattern(s) being scale and rotation invariant within a complex multiplicative constant, said apparatus comprising:

15

means for correlating said image with said pattern; and

means for locating one or more magnitude peaks, said peak(s) corresponding to center position(s) of basis pattern(s) having the same parameters as that of said pattern.

20

39. Apparatus as claimed in claim 31, with said pattern and said basis pattern(s) being of the form:

$$g_{mk}(r, \theta) = r^{i\alpha_m + p} e^{ik\theta},$$

with k , p and α_m being parameters of said pattern and basic pattern(s), r being a polar distance defined in terms of the Cartesian axes of said image as $r^2 = x^2 + y^2$ and $\theta = \tan^{-1} \left[\frac{y}{x} \right]$.

5 40. Apparatus as claimed in claim 39, further comprising means for removing regions of said pattern having frequencies above a predetermined frequency.

41. Apparatus as claimed in claim 39 to 40, further comprising means for decoding information from at least one of said parameters, said peak position(s), an amplitude or
10 relative phase of said peak(s).

42. Apparatus as claimed in any one of claims 38 or 41, further comprising means for de-emphasising regions of said pattern corresponding with regions of said image having low intensity variation.

15

43. Apparatus of adding registration marks to an image, said apparatus comprising:
means for mathematically adding a plurality of basis patterns to said image,
wherein said basis patterns are scale and rotation invariant within a complex
multiplicative constant, and at least two of basis patterns are added with different offset
20 relative to a center of said image.

44. Apparatus as claimed in claim 43, wherein said basis patterns are of the form:

$$g_{mk}(r, \theta) = r^{i\alpha_m + p} e^{ik\theta},$$

with k and α_m being parameters of said basic patterns, r being a polar distance defined in terms of the Cartesian axes of said image as $r^2 = x^2 + y^2$ and $\theta = \tan^{-1} \left[\frac{y}{x} \right]$.

45. Apparatus as claimed in claim 44, wherein at least one parameter k or α_m of a first
5 basis pattern is different to that of a second basis pattern.

46. Apparatus as claimed in any one of claims 43 to 45, further comprising means for
de-emphasising regions of said basis patterns corresponding with regions of said image
having low intensity variation.

10

47. Apparatus of registering an image having a watermark embedded, said watermark
comprising a plurality of basis patterns, said apparatus comprising:

means for correlating said image with a pattern; said pattern and said basis
patterns being scale and rotation invariant within a complex multiplicative constant;

15 means for locating peak positions, said peak positions corresponding to center
positions of basis patterns having the same parameters as that of said pattern;

means for comparing said peak positions with predetermined positions from an
original image; and

means for transforming said image to invert linear transformations.

20

48. Apparatus as claimed in claim 47, said pattern and said basis patterns being of the
form:

$$g_{mk}(r, \theta) = r^{i\alpha_m + p} e^{ik\theta},$$

with k , p and α_m being parameters of said pattern and basic patterns, r being a polar distance defined in terms of the Cartesian axes of said image as $r^2 = x^2 + y^2$ and $\theta = \tan^{-1} \left[\frac{y}{x} \right]$.

5 49. Apparatus as claimed in claim 48 further comprising means for removing regions of said pattern having frequencies above a predetermined frequency.

50. Apparatus as claimed in any one of claims 47 to 49, further comprising means for de-emphasising regions of said pattern corresponding with regions of said image having
10 low intensity variation.

51. Apparatus as claimed in any one of claims 30 to 50, wherein said basis pattern(s) is distorted using amplitude soft thresholding.

15 52. Apparatus of watermarking an audio stream, said apparatus comprising:
means for mathematically adding at least one basis signal to said audio stream, wherein said basis signal(s) is scale invariant within a complex multiplicative constant.

53. Apparatus as claimed in claim 52 wherein said basis signal(s) is of the form:

20
$$g_m(t) = |t|^{i\alpha_m + p},$$

with α_m and p being parameters of said basic signal(s) and t being a time in said audio stream.

54. Apparatus as claimed in claim 53 further comprising means for removing region(s) of said basis signal(s) having frequencies above a predetermined frequency.

55. Apparatus as claimed in any one of claims 52 to 54, further comprising means for
5 de-emphasising regions of said basis signal(s) corresponding with regions of said audio stream having low amplitude variation.

56. Apparatus of detecting a signal in a watermark of an audio stream, said watermark comprising at least one basis signal, with said signal and said basis signal(s) being scale
10 invariant within a complex multiplicative constant, said apparatus comprising:

means for correlating said audio stream with said signal; and

means for locating one or more magnitude peaks, said peak(s) corresponding to center position(s) of basis signal(s) having the same parameter as that of said signal.

15 57. Apparatus as claimed in claim 56, with said signal and said basis signal(s) being of the form:

$$g_m(t) = |t|^{i\alpha_m + p},$$

with α_m being a parameters of said signal and basic signal(s) and t being a time in said audio stream.

20

58. Apparatus as claimed in claim 57 further comprising means for removing regions of said signal having frequencies above a predetermined frequency.

59. Apparatus as claimed in any one of claims 56 to 58, further comprising means for emphasising regions of said signal corresponding with regions of said audio stream having low intensity variation.

5 60. A method as claimed in any one of claims 1 to 21, wherein said basis pattern(s) is distorted using amplitude soft thresholding.

61. A method substantially as described herein with reference to the accompanying drawings.

10

62. Apparatus substantially as described herein with reference to the accompanying drawings.

Dated this TWENTY-SEVENTH day of OCTOBER 2000

15

CANON KABUSHIKI KAISHA

Patent Attorneys for the Applicant

Spruson&Ferguson





Fig. 1




real part

imaginary part

Fig. 2A

Fig. 2B



real part

imaginary part

Fig. 3A

Fig. 3B






Fig. 5

**Fig. 4**



501



Fig. 6





Fig. 7A



502



Fig. 7B





Fig. 8






Fig. 9






Fig. 10A




Fig. 10B




Fig. 11A




Fig. 11B





Fig. 12



RECEIVED
1961
JAN 11 1961
FEDERAL BUREAU OF INVESTIGATION
U.S. DEPARTMENT OF JUSTICE

Fig. 13




Fig. 14




Fig. 15